

PRESET COUNTER CT 5



- 0 to 99,999 counts selectable with Thumb Wheel Switch
- Digital display with up counting
- LED indication for input signal and relay status.
- Input signal from proximity switch or limit switch
- Single change over relay output rated for 5 Amps @ 250V AC
- Counting speed up to 100 Hz maximum.
- External RESET contacts
- Battery back up.
- Panel mounting arrangement.
- Available in 240V AC and 110V AC models

Function	Programmable Annunciator with 16 windows, 16 inputs and 16 outputs
Rated Supply	110 VAC to 240 VAC
Operating Voltage	+ 10% of rated voltage
Rated Frequency	50 Hz + 5%
Power Consumption	AC approx. 30 VA/6W
Control Output *	1 C/O rated for 10A @ 250 VAC/28 V DC resistive load
Number of Windows	16
Window Size	32X32(LXW)
Legend Size	27X27(LXW)
Humidity	Up to 85% RH @ 400C
Connections	Screw type terminals with self lifting clamps.
Ambient temperature	Operation : -100C to + 550C Storage : -250C to +800C
Insulation Resistance	> 100M ohms @ 500V DC
Service Life (under no load)	106 operations minimum
Electrical Life (under full load)	105 operations minimum
Dimension *	Master module : 285 X 180.5 X 82 mm (LXWXD) Input module : 195 X 90 X 58.5 mm (LXWXD) Output module : 375 X 90 X 58.5 mm (LXWXD)



DIGITAL PROMOTERS
(INDIA) PRIVATE LIMITED

502 & 505, Vishal Bhawan, 95 Nehru Place, New Delhi-110 019, INDIA
 Ph. : 41618100 (3 Lines), 011-26418118 Fax : 26437849
 Email : digitalpromoters@gmail.com • info@digitalpromoters.com
 Website : www.DigitalPromoters.com

